Power Optimizer

P605* / P650 / P701 / P730 / P800p / P801 / P850 / P950 / P1100



POWEROPTIMIZER

PV power optimization at the module level The most cost-effective solution for commercial and large field installations

- Specifically designed to work with SolarEdge inverters
- Up to 25% more energy
- Superior efficiency (99.5%)
- Balance of System cost reduction; 50% less cables, fuses and combiner boxes, over 2x longer string lengths possible

- Fast installation with a single bolt
- Advanced maintenance with module-level monitoring
- Module-level voltage shutdown for installer and firefighter safety
- Use with up to two PV modules connected in series or in parallel



/ Power Optimizer

P605* / P650 / P701 / P730

Power Optimizer Model (Typical Module Compatibility)	P605* (for 1 x high power PV module)	P650 (for up to 2 x 60- cell PV modules)	P701 (for up to 2 x 60/120-cell PV modules)	P730 (for up to 2 x 72-cell PV modules)								
INPUT												
Rated Input DC Power ⁽¹⁾	605	650	700	730	W							
Connection Method	Single input for series connected modules											
Absolute Maximum Input Voltage (Voc at lowest temperature)	65 96 125											
MPPT Operating Range	12.5 - 65 12.5 - 80 12.5 - 105											
Maximum Short Circuit Current per Input (Isc)	14	11	11.75	11	Adc							
Maximum Efficiency	99.5											
Weighted Efficiency	98.6											
Overvoltage Category		II										
OUTPUT DURING OPERATION (POWER OF	PTIMIZER CONNECTE	D TO OPERATING SO	OLAREDGE INVER	TER)								
Maximum Output Current	15											
Maximum Output Voltage		80			Vdc							
OUTPUT DURING STANDBY (POWER OPTIM	IZER DISCONNECTED	FROM SOLAREDGE II	NVERTER OR SOLA	REDGE INVERTER	OFF)							
Safety Output Voltage per Power Optimizer												
STANDARD COMPLIANCE												
EMC	FCC Part 15 Class B, IEC61000-6-2, IEC61000-6-3											
Safety	IEC62109-1 (class II safety)											
RoHS	Yes											
Fire Safety	VDE-AR-E 2100-712:2013-05											
INSTALLATION SPECIFICATIONS												
Compatible SolarEdge Inverters	Three phase inverters SE16K & larger	Three phase inverters SE15K & larger	ers SE16K & larger									
Maximum Allowed System Voltage		1000										
Dimensions (W x L x H)	129 x 153 x 52 / 5.1 x 6 x 2	129 x 153 x 42.5 / 5.1 x 6 x 1.7		129 x 153 x 49.5 / 5.1 x 6 x 1.9	mm / in							
Weight	1064 / 2.3	2.3 834 / 1.8 933 / 2.1										
Input Connector		MC4 ⁽²⁾										
Input Wire Length	0.16 / 0.52 0.16 / 0.52 0.16 / 0.52 0.16 0.16 0.52 0.16 0.52 0.16 0.16 0.52 0.16 0.16 0.52 0.16 0.16 0.52 0.16 0.16 0.52 0.16 0.16 0.16 0.52 0.16 0.16 0.16 0.16 0.16 0.16 0.16 0.16											
Output Connector	MC4											
	Portrait Orientation: 1.4 / 4.5	Portrait Orientation: 1.2 / 3.9	-									
Output Wire Length	- Landscape Orientation: 1.8 / 5.9 Landscape Orientation: 2.2 /											
Operating Temperature Range ⁽⁴⁾	-40 to +85 / -40 to +185											
Protection Rating	IP68 / NEMA6P											
Relative Humidity	0 - 100											

^{*} P605 is not currently available in Europe

⁽¹⁾ Rated power of the module at STC will not exceed the power optimizer "Rated Input DC Power". Modules with up to +5% power tolerance are allowed

⁽²⁾ For other connector types please contact SolarEdge

⁽³⁾ Longer inputs wire length are available for use with split junction box modules. (For 0.9m/2.95ft order P730-xxxLxxx)

⁽⁴⁾ For ambient temperature above +70°C / +158°F power de-rating is applied. Refer to Power Optimizers Temperature De-Rating Technical Note for more details

/ Power Optimizer

P800p / P801 / P850 / P950 / P1100

Power Optimizer Model (Typical Module Compatibility)	P800p (for up to 2 x 96-cell 5" PV modules)	P801 (for up to 2 x 72/144-cell PV modules)	P850 (for up to 2 x high power or bi- facial modules)	P950 (for up to 2 x high power or bi-facial modules)	P1100 (for up to 2 x high power or bi- facial modules)							
INPUT		'			'	'						
Rated Input DC Power ⁽¹⁾	800	800	850	950	1100	W						
Connection Method	Dual input for independently connected of Single input for series connected modules											
Absolute Maximum Input Voltage (Voc at lowest temperature)	83 125											
MPPT Operating Range	12.5 - 83	12.5 - 83 12.5 - 105										
Maximum Short Circuit Current per Input (Isc)	7	11.75	12	2.5	14	Adc						
Maximum Efficiency			99.5			%						
Weighted Efficiency	98.6											
Overvoltage Category	II											
OUTPUT DURING OPERATION	(POWER OPTIMIZ	ER CONNECTE	D TO OPERATING S	SOLAREDGE INVER	TER)							
Maximum Output Current	18	15		18		Adc						
Maximum Output Voltage		80										
OUTPUT DURING STANDBY (PC	WER OPTIMIZER DI	SCONNECTED	FROM SOLAREDGE	INVERTER OR SOLA	REDGE INVERTER O	FF)						
Safety Output Voltage per Power Optimizer 1 ± 0.1												
STANDARD COMPLIANCE	'											
EMC		FCC Pa	ert 15 Class B, IEC61000-6-2,	. IFC61000-6-3								
Safety			IEC62109-1 (class II safe									
RoHS			Yes									
Fire Safety		VDE-AR-E 2100-712:2013-05										
INSTALLATION SPECIFICATION	NS											
Compatible SolarEdge Inverters	Three phase inverters SE16K & larger Three phase inverters SE25K & larger SE25K & larger											
Maximum Allowed System Voltage			1000			Vdc						
Dimensions (W x L x H)	129 x 168 x 59 / 129 x 153 x 49.5 / 129 x 162 x 59 / 5.1 x 6.4 x 2.32											
Weight	1064 / 2.3 933 / 2.1 1064 / 2.3											
Input Connector			MC4 ⁽²⁾									
Input Wire Length	0.16 / 0.52	0.16 / 0.52 , 0.9 / 2.95	0.16 / 0.52, 0.9 / 2.95, 1.3 / 4.26, 1.6 / 5.24 ⁽³⁾	0.16 / 0.52, 1.3 / 4.26, 1.6 / 5.24 ⁽³⁾	0.16 / 0.52, 0.9 / 2.95 1.3 / 4.26, 1.6 / 5.24 ⁽³⁾	m / ft						
Output Connector	MC4											
Output Wire Length	Portrait Orientation: 1.2 / 3.9											
	Landscape Orientation: 2.4 / 7.8 Landscape Orientation: 2.2 / 7.2											
Operating Temperature Range ⁽⁴⁾	-40 to +85 / -40 to +185											
Protection Rating	IP68 / NEMA6P											
Relative Humidity	0 - 100											

⁽¹⁾ Rated power of the module at STC will not exceed the power optimizer "Rated Input DC Power". Modules with up to +5% power tolerance are allowed

⁽⁴⁾ For ambient temperature above +70°C / +158°F power de-rating is applied. Refer to Power Optimizers Temperature De-Rating Technical Note for more details

PV System Design Using a SolarEdge Inverter (5)(6)(7)(8) Three Phase SE15K and larger				Three Phase SE16K and larger								Three Phase for 277/480V grid								
Compatible Power	Optimizers	P650	P605*	P650	P701	P730	P801	P800p/ P850	P950	P1100	P605*	P650	P701	P730	P801	P800p/ P850	P950	P1100		
Minimum String Length	Power Optimizers	14																		
	PV Modules	27	14 27						14	27										
Maximum String	Power Optimizers	30																		
Length	PV Modules	60	30 60					30	60											
Maximum Nomina	Power per String		11250 ⁽⁹⁾ 13500 ⁽⁹⁾					12750 ⁽¹⁰⁾ 15300					15300(10)		W					
Parallel Strings of I Orientations	Different Lengths or		Yes																	

⁽⁵⁾ P650/P701/P730/P801 can be mixed in one string, and P850/P800p/P950/P1100 can also be mixed in one string. It is not allowed to mix P650/P701/P730/P801 with P850/P800p/P950/P1100, nor is it allowed to mix P650-P1100 with P370-P505 in one string. P605 cannot be mixed with any other power optimizer in the same string

⁽²⁾ For other connector types please contact SolarEdge

⁽³⁾ Longer inputs wire length are available for use with split junction box modules. (For 0.9m/ 2.95ft order P801/ P850/P1100-xxxLxxx. For 1.3m/2.95ft order P850/P950/P1100 -xxxXxxx. For 1.6m/5.24ft order P850/P950/P1100

⁽⁶⁾ In a case of odd number of PV modules in one string it is allowed to install one P650/P701/P730/P850/P800p/P801/P950/P1100 power optimizer connected to one PV module. When connecting a single module to the P800p seal the unused input connectors with the supplied pair of seals

⁽⁷⁾ Power optimizers intended for use with two PV modules each (2:1 connection), can be used with a single PV module (1:1 connection), as long as the entire string uses 1:1 connections

⁽⁸⁾ For SE15k and above, the minimum DC power should be 11kW (9) For the 230/400V grid: With P605/P650/P701/P730/P801 up to 13,500W per string may be installed, with P850/P800p up to 15,750W and with P950/P1100 up to 18,500W per string may be installed when the maximum power difference between each string is 2,000W.For P950/P1100, minimum two string are required for SE16K-SE27.6K inverters, and for SE30K and above minimum three string are required

⁽¹⁰⁾ For the 277/480V grid: With P605/650/P701/P730/P801 up to 15,000W per string may be installed, with P850/P800p up to 17,550W and with P950/P1100 up to 20,300W per string may be installed when the maximum power difference between each string is 2,000W.For P950/P1100, minimum three string are required for SE33.3K and SE40K inverters

SolarEdge is a global leader in smart energy technology. By leveraging world-class engineering capabilities and with a relentless focus on innovation, SolarEdge creates smart energy solutions that power our lives and drive future progress.

SolarEdge developed an intelligent inverter solution that changed the way power is harvested and managed in photovoltaic (PV) systems. The SolarEdge DC optimized inverter maximizes power generation while lowering the cost of energy produced by the PV system.

Continuing to advance smart energy, SolarEdge addresses a broad range of energy market segments through its PV, storage, EV charging, UPS, and grid services solutions.

- **f** SolarEdge
- @SolarEdgePV
- @SolarEdgePV
- SolarEdgePV
- in SolarEdge
- info@solaredge.com
 info@solaredge.com

solaredge.com

© SolarEdge Technologies, Ltd. All rights reserved. SOLAREDGE, the SolarEdge logo, OPTIMIZED BY SOLAREDGE are trademarks or registered trademarks of SolarEdge Technologies, Inc. All other trademarks mentioned herein are trademarks of their respective owners. Date: 12/2020/V01/EN ROW. Subject to change without notice.

Cautionary Note Regarding Market Data and Industry Forecasts:This brochure may contain market data and industry forecasts from certain third-party sources. This information is based on industry surveys and the preparer's expertise in the industry and there can be no assurance that any such market data is accurate or that any such industry forecasts will be achieved. Although we have not independently verified the accuracy of such market data and industry forecasts, we believe that the market data is reliable and that the industry forecasts are reasonable.

